

IPOD-EL2MPIR50 User's Manual

Version 3.5.1

Welcome

Thank you for purchasing our Network camera!

This user's manual is designed to be a reference tool for your system.

Please read the following safeguard and warnings carefully before you use this series product!

Please keep this user's manual well for future reference!

Important Safeguards and Warnings

1 . Electrical safety

All installation and operation here should conform to your local electrical safety codes.

The power shall conform to the requirement in the SELV (Safety Extra Low Voltage) and the Limited power source is rated 12V DC in the IEC60950-1. This series product supports PoE too. **Please note: Do not connect these two power supplying sources to the device at the same time; it may result in device damage!**

We assume no liability or responsibility for all the fires or electrical shock caused by improper handling or installation.

We are not liable for any problems caused by unauthorized modification or attempted repair.

2 . Transportation security

Heavy stress, violent vibration or water splash are not allowed during transportation, storage and installation.

3 . Installation

Do not apply power to the camera before completing installation.

Please install the proper power cut-off device during the installation connection.

Always follow the instruction guide the manufacturer recommended.

4 . Qualified engineers needed

All the examination and repair work should be done by the qualified service engineers.

We are not liable for any problems caused by unauthorized modifications or attempted repair.

5 . Environment

This series network camera should be installed in a cool, dry place away from direct sunlight, inflammable, explosive substances and etc.

Please keep it away from the electromagnetic radiation object and environment.

Please make sure the CCD (CMOS) component is out of the radiation of the laser beam device.

Otherwise it may result in CCD (CMOS) optical component damage.

Please keep the sound ventilation.

Do not allow the water and other liquid falling into the camera.

Thunder-proof device is recommended to be adopted to better prevent thunder.

The grounding studs of the product are recommended to be grounded to further enhance the reliability of the camera.

6. Daily Maintenance

Please shut down the device and then unplug the power cable before you begin daily maintenance work.

Do not touch the CCD (CMOS) optic component. You can use the blower to clean the dust on the lens surface.

Always use the dry soft cloth to clean the device. If there is too much dust, please use the water to dilute the mild detergent first and then use it to clean the device. Finally use the dry cloth to clean the device.

Please put the dustproof cap to protect the CCD (CMOS) component when you do not use the camera.

7. Accessories

Be sure to use all the accessories recommended by manufacturer.

Before installation, please open the package and check all the components are included.

Contact your local retailer ASAP if something is broken in your package.

Accessory Name	Amount
Network Camera Unit	1
Quick Start Guide	1
Installation Accessories Bag	1
CD	1

Table of Contents

1	General Introduction	1
1.1	Overview	1
1.2	Features	1
1.3	Specifications	2
1.4	Factory Default Setup	3
2	Structure	8
2.1	Components	8
2.2	Framework and Dimension	8
3	Device Installation	10
3.1	Installation Steps	10
3.2	Restore Factory Default Setup Introduction	12
4	Quick Configuration Tool	13
4.1	Overview	13
4.2	Operation	13
5	Web Operation	15
5.1	Network Connection	15
5.2	Login and Logout	15
6	FAQ	17
	Appendix Toxic or Hazardous Materials or Elements	18

1 General Introduction

1.1 Overview

This series network camera integrates the traditional camera and network video technology. It adopts video data collection, transmission together. It can connect to the network directly without any auxiliary device.

This series network camera uses standard H.264 video compression technology, which maximally guarantees the video quality.

It supports the IR night vision function. In the night environments, the device can use the IR light to highlight the object which is suitable for the surveillance function in the low illumination environments. The waterproof design conforms to the IP 66 level. It has the sound waterproof function suitable for use in the outdoor environments.

It can be used alone or used in a network area. When it is used lonely, you can connect it to the network and then use a network client-end. Due to its multiple functions and various uses, this series network camera is widely used in many environments such office, bank, road monitor and etc.

1.2 Features

User Management	● Different user rights for each group, one user belongs to one group. ● The user right shall not exceed the group right.
Storage Function	● Support central server backup function in accordance with your configuration and setup in alarm or schedule setting ● Support record via Web and the recorded file are storage in the client-end PC. ● Support network storage function such as FTP.
Network Monitor	● Network camera supports one-channel video data transmit to network terminal and then decode. Delaying time is within 270ms (network bandwidth support needed) ● Max supports 20 connections. ● Adopt the following video transmission protocol: HTTP, TCP, UDP, MULTICAST, RTP/RTCP, RTSP and etc. ● Support web access.
Network Management	● Realize network camera configuration and management via Ethernet. ● Support device management via web or client-end.
Power	● External power adapter DC 12V. ● Support PoE. Warning ! Do not connect these two power supplying sources to the device at the same time; it may result in device damage!
Assistant Function	● Log function ● Support system resource information and running status real-time display. ● Day/Night mode auto switch. ● Support picture parameter setup such as electronic shutter and gain setup. ● Support motion detect. ● Backlight compensation: screen auto split to realize backlight compensation to adjust the bright. ● Support video watermark function to avoid vicious video modification. ● Built-in IR light. Support IR night vision. ● The enclosure conforms to the IP 66 protection. Has the waterproof function.

1.3 Specifications

Please refer to the following sheet for network camera performance specification.

Model Parameter		IPOD-EL2MPIR50	
System	Main Processor	TI Davinci high performance DSP	
	OS	Embedded LINUX	
	System Resources	Support real-time network, local record, and remote operation at the same time.	
	User Interface	Remote operation interface such as WEB, DSS, PSS	
	System Status	Bit stream statistics, log, and software version.	
Video Parameter	Image Sensor	1/3-inch CMOS	1/2.8-inch CMOS
	Pixel	1920(H)*1080(V)	2048(H)*1536(V)
	Day/night	Support IR-CUT switch	
	Gain Control	Fixed/Auto	
	White Balance	Manual/Auto	
	Exposure Mode	Manual/Auto PAL: It ranges from 1/3 to 1/10000 NTSC: It ranges from 1/4 to 1/10000	
	Video Compression Standard	H.264/JPEG/MJPEG	
	Video Frame Rate	PAL: Main stream(1920*1080@25fps), extra stream,(704*576@25fps)	PAL: Main stream(2048*1536@18fps), extra stream(704*576@18fps)
		NTSC: Main stream(1920*1080@30fps), extra stream,(704*576@30fps)	NTSC: Main stream(2048*1536@20fps), extra stream(704*576@20fps)
	Video Bit Rate	48k~8192kbps Bit rate is adjustable. Support customized setup.	
	Video Flip	Support mirror. Support flip function.	
	Snapshot	Max 1f/s snapshot. File extension name is JPEG.	
	Privacy Mask	Supports max 4 privacy mask zones	
	Video Setup	Support parameter setup such as bright, contrast.	
	Video Information	Channel title, time title, motion detect, camera masking.	
	Lens	2.8mm, 3.6mm, 6mm, 8mm. Fixed focus.	3.6mm, 6mm, 8mm. Fixed focus.
	Lens Interface	M12. Lens is the default accessories	

Video		Motion Detect	396 (18*22) detection zones; sensitivity level ranges from 1 to 6 (The 6 th level has the highest sensitivity) Activation event: video storage, image snapshot, log, email function and etc.	
Record and Backup	Record Priority		Manual>External alarm >Video detect>Schedule	
	Storage Management		Support FTP storage.	
Network	Wire Network		1-ch 10/100 M Ethernet , RJ45 port	
	Network Protocol		HTTP, TCP/IP, ARP, RTSP, RTP,UDP, RTCP, SMTP, FTP, DHCP, DNS, DDNS, PPPOE, IPv4/6, SNMP, UPNP, NTP	
	Remote Operation		Monitor, system setup, file download, log information, maintenance , upgrade and etc	
	Restore Default Setup		Built-in Reset button	
	IR light		IR light 20M.	IR light 25M.
General Parameter	Power		DC12V power and PoE. Warning ! Do not connect these two power supplying sources to the device at the same time; it may result in device damage!	
	Power Consumption		4.5W MAX	
	Working Temperature		-10℃~+60℃	
	Working Humidify		10%~90%	
	Dimensions(mm)		Φ 113×86	
	Weight		280g(Excluding box)	
	Installation		Fixed on the wall, ceiling and etc.	

1.4 Factory Default Setup

Please refer to the following sheet for factory default setup information.

Setup	Item	Default Setup		
				IPOD-EL2MPIR50
Camera	Conditions	Brightness	50	
		Contrast	50	
		Sharpness	50	
		Saturation	50	
		Anti-flicker	Outdoor	
		Gain Mode	Auto	
		Gain Limit	0~50	
		Scene Mode	Auto	
		Day/night Mode	Auto	
		BLC	Off	
		Mirror	Off	
		Flip	Off	

Setup		Item			Default Setup		
							IPOD-EL2MPIR50
Net work	Video	Video bit stream	Main Stream	Bit stream type	General		
				Encode mode	H.264		
				Resolution	1080P(1920*1080)		
				Frame Rate(FPS)	PAL: 25 NTSC:30		
				Bit Rate Type	CBR		
				Recommend ed Bit	3584-8192 Kb/S		
				Bit Rate	8192		
				I Frame interval	50		
				Watermark	Enable		
				Watermark character	DigitalCCTV		
			Sub Stream	Enable	Enable		
				Bit stream type	General		
				Encode mode	H.264B		
				Resolution	CIF(352*288)		
				Frame Rate(FPS)	PAL: 25 NTSC:30		
				Bit Rate Type	CBR		
				Recommend ed Bit	192-1024Kb/S		
				Bit Rate	1024		
				I Frame interval	50		
		Snapshot	Snapshot Type	General			
			Image Size	1080P （1920*1080）			
			Quality	Better			
			Interval	1s			
		Video Overlay	Privacy Mask	Disable			
			Channel Title	Enable			
			Time Title	Enable			
		Path	Snapshot Path	C:\PictureDownload			
			Record Path	C:\RecordDownload			
TCP/IP	Host Name	IPC					
	Ethernet Card	Wire(Default)					

Setup	Item		Default Setup		
					IPOD-EL2MPIR50
		Mode	Static		
		Mac Address	Device MAC address when it is shipped out of the factory		
		IP Version	IPV4		
		IP Address	192.168.1.108		
		Subnet Mask	255.255.255.0		
		Default Gateway	192.168.1.1		
		Preferred DNS	8.8.8.8		
		Alternate DNS	8.8.8.8		
		Enable ARP/Ping set device IP address service	Enable		
	Connection	Max Connection	10		
		TCP Port	37777		
		UDP Port	37778		
		HTTP Port	80		
		RTSP Port	554		
		Enable HTTP	Disable		
		HTTPs Port	443		
	PPPoE	Enable	Disable		
		Username	none		
		Password	N/A		
	DDNS	Server Type	Disable, CN99 DDNS		
		Server IP	none		
		Server Port	80		
		Domain Name	none		
		User	none		
		Password	****		
		Update Period	10 minutes		
	IP Filter	Trusted sites	Disable		
	SMTP(Email)	SMTP Server	none		
		Port	25		

Setup	Item		Default Setup		
					IPOD-EL2MPIR50
			Anonymity	Disable	
			User Name	anonymity	
			Password	****	
			Sender	none	
			Authenticatio n (Encryption mode)	N/A	
			Title (Subject)	IPC Message	
			Attachment	N/A	
			Mail Receiver	0 seconds	
			Email Test	Disable, interval=60 seconds	
			UPnP	Enable UPnP	Disable
	SNMP		SNMP Port	161	
			Read Community	public	
			Write Community	private	
			Trap Address	N/A	
			Trap Port	162	
			SNMP Version	SNMP v1:Disable SNMP v2:Disable SNMP v3:Disable	
	Bonjour		Enable	Enable	
			Server Name	Device factory SN	
	Multicast		Multicast Address	239.255.42.42	
			Port	36666	
	QoS		Real-time Monitor	0	
			Command	0	
Event	Video detect	Motion Detect		Enable	Disable
				Anti-dither	5 seconds
				Sensitivity	3
				Record Channel	Enable
				Record Delay	10 seconds
				Send Email	Disable
				Snapshot	Disable
				Video	Enable

Setup	Item			Default Setup		
						IPOD-EL2MPIR50
		Masking	Record Channel	Enable		
			Record Delay	10 seconds		
			Send Email	Disable		
			Snapshot	Disable		
Storage	Storage	FTP	Enable FTP	Disable		
			Server IP	N/A		
			Port	21		
			Username	anonymity		
			Password	N/A		
			Remote path	share		
			Emergency (Local)	Disable		
	Record Control		Pack Duration	8 minutes		
			Pre-record	5 seconds		
			Disk Full	Overwrite		
			Record Mode	Auto		
			Bit Stream	Main Stream		
System	General	Local Host	Device No	Device MAC address		
			Language	English		
			Video Standard	PAL	PAL/NTSC	
		Date and time	Date Format	Y-M-D		
			Time Format	24H		
			Time Zone	GMT+08:00		
			System Time	Sync		
			DST	Disable		
			DST Type	Week		
			Start Time	00:00:00 of the first Sunday of the month		
			End Time	00:00:00 of the second Monday of the month		
			NTP	Disable		
			NTP Server	clock.isc.org		
			Port	37		
			Update Period	10 minutes		
	Auto Maintenance	Auto Reboot	Enable			
		Auto Delete Old Files	Disable			

2 Structure

2.1 Components

You can refer to the following figure for multiple-function combination cable information. See Figure 2-1.




Figure 2-1

Please refer to the following sheet for detailed information.

Component	Component Name
Component 1	Device lens
Component 2	Dome body
Component 3	Dome enclosure

No.	Port	Name	Connector	Note
4	LAN	Network port	Ethernet	To connect to standard Ethernet.
5	DC12V	DC power 12V		To connect to DC12V power supply.

2.2 Framework and Dimension

Please refer to the following two figures for dimension information. The unit is mm. See Figure 2-2 and Figure 2-3.




Figure 2-2




Figure 2-3

3 Device Installation

3.1 Installation Steps

Important

Before the installation, please make sure the installation environments can at least support 3x weight of the camera.

Please follow the steps listed below to install the device. Please refer to Figure 3-1 for reference.

Step 1

Turn clockwise to remove the decoration ring from the snap joints.

Step 2

Please take the installation position map in the accessories bag, and then paste it on the ceiling or the wall according to your monitor area requirements. Draw and then dig three plastic expansion bolts holes in the installation surface and then insert three expansion bolts in the holes. Secure these three bolts firmly. Please draw the cable out from the cable exit when you install the device.

Step 3

Adjust the device installation pedestal to the proper position and then line up the three screw holes in the device pedestal to the three plastic expansion bolt holes in the installation position. Put the three self-tapping screws in the three plastic expansion bolts firmly. Loosen the M3X8 cross recessed pan head slot screw of the pedestal to unfasten the preforming. (Do not remove, loosen a little bit will be OK.). Adjust the lens to the proper monitor angle and then use the original preforming to turn the M3X8 cross recessed pan head slot screw back.

Step4

Line up the three spigots of the decoration ring to the jags from the bottom to the top and then turn clockwise until you hear a clear sound "KA". Now the installation is complete.




Figure 3-1

Important

Please pay attention to the dome camera direction when you are installing. Please refer to the following figure for detailed information. See Figure 3-2.




Figure 3-2

Note

This series product supports two cable exits. One is from the bottom and the other is from the side. Please refer to the following figure for cable exit from the side information.




Figure 3-3

Please earth the GND port of the device to enhance the device reliability. The GND port is near the cable exit port on the rear of the dome. The GND screw uses the M2X5 pan screw.




Figure 3-4

3.2 Restore Factory Default Setup Introduction

Important

Please use RESET button when device is running.

Step1

Please refer to step1 and step2 in chapter 3.1 to loose the dome body. Push a little bit; you can take the dome body from the gland cover.

Step2

Take the dome body out and then turn the top cover hard to remove.

Step3

Slightly press the RESET button to complete the reset function. See Figure 3-5.

Step4

Turn the top cover back to the original position. Please make sure it reaches the original position, otherwise it may result in water leakage!

Step5

Put the dome back to the gland cover. Please refer to step4 in chapter 3.1 to install the decoration ring back.




Figure 3-5

In the configuration tool search interface (Figure 4-1), please select a device IP address and then double click it to open the login interface. Or you can select an IP address and then click the Login button to go to the login interface. See Figure 4-3.

In Figure 4-3, you can view device IP address, user name, password and port. Please modify the corresponding information to login.

Please note the port information here shall be identical with the port value you set in TCP port in Web Network interface. Otherwise, you cannot login the device.

If you are using device background upgrade port 3800 to login, other setups are all invalid.


A Windows-style dialog box titled "Login" with a close button in the top right corner. It contains four text input fields: "IP Address:" with the value "192.168.1.108", "User Name:" with the value "admin", "Password:" with the value "*****", and "Port:" with the value "37777". At the bottom, there are two buttons: "Login" and "Cancel".

Figure 4-3

After you logged in, the configuration tool main interface is shown as below. See Figure 4-4.


A screenshot of the configuration tool main interface. At the top, there are four tabs: "Network Parameter", "PPPOE", "System Information", and "System Upgrade". The "Network Parameter" tab is selected. Below the tabs, there is a section titled "General Parameter". It contains a checkbox for "DHCP Enable" which is unchecked, and a dropdown menu for "IPv4" which is set to "IPv4". Below these, there are five text input fields: "IP Address:" with the value "192.168.1.108", "Subnet Mask:" with the value "255.255.0.0", "Gateway:" with the value "10.15.0.1", and "Mac Address:" with the value "90:02:a9:7f:d8:21". At the bottom right of the window, there are two buttons: "Save" and "Return".

Figure 4-4

For detailed information and operation instruction of the quick configuration tool, please refer to the *Quick Configuration Tool User's Manual* included in the resources CD.

5 Web Operation

This series network camera product supports the Web access and management via PC. Web includes several modules: monitor channel preview, system configuration, alarm and etc.

5.1 Network Connection

Please follow the steps listed below for network connection.

- Make sure the network camera has connected to the network properly.
- Please set the IP address, subnet mask and gateway of the PC and the network camera respectively. Network camera default IP address is 192.168.1.108. Subnet mask is 255.255.255.0. Gateway is 192.168.1.1
- Use order ping `***.***.***.***`(* network camera address) to check connection is OK or not.

5.2 Login and Logout

Open IE and input network camera address in the address bar. See Figure 5-1.




Figure 5-1

The login interface is shown as below. See Figure 5-2.

Please input your user name and password.

Default factory name is admin and password is admin.

Note: For security reasons, please modify your password after you first login.




Figure 5-2

If it is your first time to login in, system pops up warning information to ask you whether install control webrec.cab or not after you logged in for one minute. Please click OK button, system can automatically install the control. When system is upgrading, it can overwrite the previous Web too. If you can't download the ActiveX file, please check whether you have installed the plug-in to disable the control download. Or you can lower the IE security level. After you logged in, you can see the main window. See Figure 5-3.




Figure 5-3

Please refer to the Web Operation Manual included in the resource CD for detailed operation instruction.

6 FAQ

Bug	
I can not boot up the device or operate properly.	Please click RESET button for at least five seconds to restore factory default setup.
The water leakage occurred.	The unauthorized front or rear cap remove many result in water leakage. The glass front cap has sustained heavy push or strike. The waterproof plug of the rear cap becomes loosen.
IR video is poor.	Do not use the proper supplying power. The IR light can not turn on completely. The object is out of the IR distance range of current device. IR-CUT does not turn to the night mode. The photosensitive chip of the front-end can not sense the IR light.
I can not upgrade the device via network.	When network upgrade operation failed, you can use port 3800 to continue upgrade.
I can not login the client-end or the WEB.	For Windows OS 98 or Windows ME user, if you can not install the client-end or can not view after the installation. We recommend the win2000sp4 OS or install the client-end of the low version. The Active X control is blocked. The display card version shall be dx8.1 or higher. Network connection error occurred. Invalid network setup. Invalid user name or password.
I can not play the download file.	There is no player. There is no DX8.1 or higher. For the MEDIA PLAYER, there shall be Div X503Bundle.exe plugin if you play the .AVI file. For Windows XP user, you need to install the plugin DivX503Bundle.exe and ffdsho-2004 1012.exe.
To guarantee setup update	After you modified the important setup, please reboot the device via the software to make sure the setup has been updated to the storage medium.
Power adapter	The general power adapter can work ranging from 0℃ to 40 ℃. The device may result in unstable power supply when the temperature exceeds the working temperature. Please replace an industry-level power adapter if you are using in the harsh environments.

Appendix Toxic or Hazardous Materials or Elements

Component Name	Toxic or Hazardous Materials or Elements					
	Pb	Hg	Cd	Cr VI	PBB	PBDE
Circuit Board Component	○	○	○	○	○	○
Device Case	○	○	○	○	○	○
Wire and Cable	○	○	○	○	○	○
Packing Components	○	○	○	○	○	○
Accessories	○	○	○	○	○	○

O: Indicates that the concentration of the hazardous substance in all homogeneous materials in the parts is below the relevant threshold of the SJ/T11363-2006 standard.

X: Indicates that the concentration of the hazardous substance of at least one of all homogeneous materials in the parts is above the relevant threshold of the SJ/T11363-2006 standard. During the environmental-friendly use period (EFUP) period, the toxic or hazardous substance or elements contained in products will not leak or mutate so that the use of these (substances or elements) will not result in any severe environmental pollution, any bodily injury or damage to any assets. The consumer is not authorized to process such kind of substances or elements, please return to the corresponding local authorities to process according to your local government statutes.

Note

- This user's manual is for reference only. Slight difference may be found in user interface.
- All the designs and software here are subject to change without prior written notice.
- All trademarks and registered trademarks mentioned are the properties of their respective owners.
- If there is any uncertainty or controversy, please refer to the final explanation of us.
- Please visit our website for more information.